



# ICT POWER BASE STATIONS

## TAT1 BASE STATION FOR TAIT T2000II RADIO

### MODEL NUMBERS

Base Station Cover:  
BASE-TAT1

Power Supply:

ICT12012-10AG (10 Amp)

ICT12012-11AG (11 Amp)

ICT12012-12AG (12 Amp)

Complete Station:

CS120-10AG/TAT1 (10 Amp)

CS120-11AG/TAT1 (11 Amp)

CS120-12AG/TAT1 (12 Amp)

NOTE: Mobile radios sold separately

### FEATURE HIGHLIGHTS

Attractive Finish

Lightweight

Durable Design

Sleek Profile

Easy Installation

Can Be Sold Separately



### PRODUCT INFORMATION

The ICT Base Station Series provides a sleek, mobile radio base station. These covers are individually customized to fit various radio models. The ICT Base Station Series covers and ICT Comm Series power supplies may be purchased separately or as a Complete Base Station (power supply assembled with cover).

The complete station incorporates an ICT switching power supply, which is factory assembled in Canada, with a base station cover. The complete station provides a sleek, compact mobile radio base station housing individually customized to Tait mobile radios.

### COMPLETE STATION SPECIFICATIONS

	10 Amp	11 Amp	12 Amp
Input Voltage Range	90 – 130 VAC	90 – 130 VAC	90 – 130 VAC
Output Voltage	13.8 VDC +/- 150 mV	13.8 VDC +/- 150 mV	13.8 VDC +/- 150 mV
Output Current (Cont.)	7.5 Amps	9.0 Amps	10.0 Amps
Output Current (Peak)	10.0 Amps	11.0 Amps	12.0 Amps
Current Limiting	10.5 Amps	11.5 Amps	12.5 Amps
Line Regulation	0.20% (90 – 103 VAC)	0.20% (90 – 103 VAC)	0.20% (90 – 103 VAC)
Load Regulation	0.75% (1.0–10 Amps)	0.50% (1.0–11 Amps)	0.80% (1.0–12 Amps)
Output Ripple (Max)	20 mV RMS	20 mV RMS	20 mV RMS
Efficiency (Min)	85%	85%	85%
Operating Temperature	-50°F to 125°F	-50°F to 125°F	-50°F to 125°F
Size ( L x W X H )	7.6" x 6.5" x 4.0"	7.6" x 6.5" x 4.0"	7.6" x 6.5" x 4.0"
Weight	3.9 lbs.	3.9 lbs.	3.9 lbs.



Innovative Circuit Technology Ltd.

Suite 700 - 20121 100A Avenue Langley, British Columbia, Canada V1M 3X6

Tel.604.888.6304 Fax.604.888.3650 [technical@ictcorporate.com](mailto:technical@ictcorporate.com) [www.ictcorporate.com](http://www.ictcorporate.com)

Every reasonable effort has been made to ensure that ICT product manuals and promotional materials accurately describe ICT product specifications and capabilities at the time of publication. However, because of ongoing improvements and updating of ICT products, ICT cannot guarantee the accuracy of printed materials after the date of publication and disclaims liability for changes, errors or omissions.

ICT LOGOS AND SLOGAN © COPYRIGHT 2005 INNOVATIVE CIRCUIT TECHNOLOGY LTD.